

## making connections beautifully

Decorative Wiring Accessories • Smart Lighting Control • Wireless Audio


#### 7G2MBSS2BL-B

### Hartland G2 | HARTLAND G2 RANGE | Power Sockets


# Item Image



## Wiring



#### **Dimensions**



| Primary Range                 | Hartland G2  |  |  |
|-------------------------------|--|--|--|
| Insert Type                   | 2 gang 13A Double Pole Switched Socket                 |  |  |
| Insert Colour                 | Black/Black  |  |  |
| EAN13 Barcode                 | 5051164004521  |  |  |
| Commodity Code                | 85363010   |  |  |
| Luckins TSI                   | 407517714  |  |  |
| Dimensions(Nominal)           | Double: Height = 87.4mm Width = 144.4mm Depth = 4.65mm |  |  |
| Weight                        | 265 GR   |  |  |
| Switched Poles                | Double   |  |  |
| Current Rating                | 13 Amp   |  |  |
| Voltage                       | 220/250V AC  |  |  |
| Maximum Load                  | 13 Amp   |  |  |
| Mains Frequency               | 50Hz   |  |  |
| IP Rating                     | IP2XD  |  |  |
| Contact Gap Minimum           | 3mm  |  |  |
| Terminal Capacity 1           | 4x2.5mm <sup>2</sup>                                   |  |  |
| Terminal Capacity 2           | 3x4mm²   |  |  |
| Terminal Capacity 3           | 2x6mm² Multi-Strand                                    |  |  |
| Terminal Capacity 4           | lx10mm²  |  |  |
| Earth Terminal Capacity 1     | 4x2.5mm²   |  |  |
| Earth Terminal Capacity 2     | 3x4mm²   |  |  |
| Earth Terminal Capacity 3     | 2x6mm² Multi-Strand                                    |  |  |
| Earth Terminal Capacity 4     | lx10mm²  |  |  |
| Product Class 1               | Must be earthed  |  |  |
| Ambient Operating Temperature | -5° to +40°C   |  |  |
| Recommended Location          | Internal Use Only                                      |  |  |
| Maximum Installation Altitude | 2000m  |  |  |
| Standard/Approval             | BS 1363-2  |  |  |
| Additional Notes              | Dual Earth: Yes  |  |  |

7G2MBSS2BL-B - Hartland G2 Matt Black 2 gang 13A Double Pole Switched Socket Black/Black



Decorative Wiring Accessories • Smart Lighting Control • Wireless Audio

# 7G2MBSS2BL-B

| Hartland G2   HARTLAND G2 RANGE   Power Sockets  |   |   |
|--|---|---|
| All products listed conform to current<br>British or European standard and the<br>product information is correct at the<br>time of going to press.   | All accessories are manufactured<br>under an accredited BS EN ISO 9001 :<br>2015 Quality Management System.   | It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice. |
| Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.   | Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes. | Correct as at 31 May 2022 09:28 AM<br>E&OE  |
| R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ T: +44 (0)1747 860088 E: info@hamilton-litestat.com www.hamilton-litestat.com Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB Registered in London No. 941624 VAT Registration No. 222 6607 84 |   | Listed in Strimble product selector selector selector   |

7G2MBSS2BL-B - Hartland G2 Matt Black 2 gang 13A Double Pole Switched Socket Black/Black